



GOLDEN STATE INSTRUMENT CO.

GS-DP500

POWER CONVERTER

Applications:

- 12VDC CCTV cameras and accessories
- Fiber Optic Transmitters
- REX PIR's
- Prox Readers, etc.

Specifications:

- Output: 1.2 Amp/12VDC.
- Built-in overload protection.
- Electronically filtered and regulated output.
- Power LED.
- High impact insulated housing.
- Compact design allows for installation variety of camera housings.
- Dimensions: 3.1"L × 1.8"W × 1"H

Installation Instructions:

1. Mount the unit in desired location.
2. Connect Yellow leads to 24VAC transformer or 24VDC source.
3. Measure output voltage and check polarity before connecting devices, in order to avoid potential damage.
4. Connect Red lead [Pos.+] and Black lead [Neg.-] to 12VDC device to be powered.
5. LED will illuminate when power is present.